



Mercusys 8-Port Gigabit Desktop Switch



Model: MS108GS

Manufacturer: MERCUSYS

EAN: 6957939001339

Product Code: 200131

R441

Certification: CE, RoHS | Networking standards: IEEE 802.3u | Networking standards: IEEE 802.3x | Housing material: Metal | Networking standards: IEEE 802.3 | Networking standards: IEEE 802.3ab | Jumbo frames support: Yes | Networking standards: IEEE 802.3i | Jumbo frames: 15000 | Basic switching RJ-45 Ethernet ports type: Gigabit Ethernet (10/100/1000) | Depth: 99.1 mm | Storage relative humidity (H-H): 5 - 95% | Store-and-forward: Yes | Rack mounting: No | Operating relative humidity (H-H): 10 - 90% | Power supply included: Yes | Networking standards: IEEE 802.3p | Manual: Yes | Stackable: No | Transmission distance (max): 0.1 km | AC input frequency: 50/60 Hz | Height: 25.2 mm | Switching capacity: 16 Gbit/s | Quick start guide: Yes | Power consumption (max): 4.22 W | Cables included: AC | Power connector: DC-in jack | Power over Ethernet (PoE): No | Fanless: Yes | Full duplex: Yes | Storage temperature (T-T): -40 - 70 °C | Width: 158 mm | Product colour: Black | Flow control support: Yes | 10G support: No | Operating temperature (T-T): 0 - 40 °C | MAC address auto-aging supported: Yes | Switch type: Unmanaged | LED indicators: Yes | DC input voltage: 5 V | MAC address table: 8000 entries | Auto-negotiation: Yes | MAC address auto-learning supported: Yes | Auto MDI/MDI-X: Yes | Power source: DC | Wall mountable: Yes | AC input voltage: 220 V | Heat dissipation: 14.348 BTU/h | Packet buffer memory: 0.5 MB | Input current: 0.6 A | Basic switching RJ-

The product information provided is for reference purposes only. Technical specifications, photos, descriptions and prices may change without prior notice. The manufacturer and seller are not responsible for possible data discrepancies or typographical errors. We recommend checking the current information before purchasing.

shop.cssi.co.za | sales@cssi.co.za | +27 (11)541-9950

45 Ethernet ports quantity: 8 | Warnings: Do not open the case or try to repair it yourself. | Warnings: Ensure the unit is adequately ventilated during operation. | Half duplex: Yes | Warnings: The product is not suitable for disposal in the regular waste bin. Take your used electronic equipment to a recycling centre in accordance with local regulations.

The product information provided is for reference purposes only. Technical specifications, photos, descriptions and prices may change without prior notice. The manufacturer and seller are not responsible for possible data discrepancies or typographical errors. We recommend checking the current information before purchasing.

shop.cssi.co.za | sales@cssi.co.za | +27 (11)541-9950