

**KEMOT
PROsinus-2000
emergency
power supply
unit a pure sine
wave inverter
with a 12V
charging
function, 230V,
2000VA/1200W**



Model: URZ3407-LFP4

Manufacturer: KEMOT

EAN: 5901890123129

Product Code: 1246423

R4,621

Supported battery type: AGM / Gel / LiFePO | Warnings: Use the appliance in well-ventilated areas to avoid overheating. | DC battery voltage: 12 V | Warnings: Keep away from sources of fire and water. | Warnings: Do not disassemble the unit housing, there may be a risk of electric shock. | Power efficiency: 85% | Battery included: No | Power protection features: Short circuit | Power protection

features: Over voltage | Height: 203 mm | Output power capacity: 2000VA | Depth: 312 mm |

The product information provided is for reference purposes only. Technical specifications, photos, descriptions and prices may change without prior notice. The manufacturer and seller are not responsible for possible data discrepancies or typographical errors. We recommend checking the current information before purchasing.

Response time: 4 ms | Output frequency: 50/60 Hz | Weight: 11 kg | USB port: No | AC outlet types: Schuko | Output operation voltage (max): 245 V | Power protection features: Overload | Input operation voltage (max): 270 V | Input operation voltage (min): 150 V | AC outlets quantity: 2 AC outlet(s) | Automatic Voltage Regulation (AVR): Yes | Input frequency: 50/60 Hz | Width: 182 mm | Product colour: Black | Waveform: Pure sine | Output operation voltage (min): 191 V | Output power: 1200 W

The product information provided is for reference purposes only. Technical specifications, photos, descriptions and prices may change without prior notice. The manufacturer and seller are not responsible for possible data discrepancies or typographical errors. We recommend checking the current information before purchasing.

itworkup.co.za | sales@itworkup.co.za | +27 (11)541-9950