

MSI PRO A520M-S motherboard



Model: PRO A520M-S

Manufacturer: MSI

EAN: 4711377465847

Product Code: 1339955

R1,831

ECC compatibility: Non-ECC | Supported memory clock speeds: 3466 | Supported memory clock speeds: 2400 | Supported memory clock speeds: 2800 | Supported memory clock speeds: 2933 | Supported memory clock speeds: 3600 | Supported memory clock speeds: 3200 | Supported memory clock speeds: 4266 | Supported memory clock speeds: 3866 | CPU fan connector: Yes | Supported memory clock speeds: 4133 | Supported memory clock speeds: 4000 | RAID levels: 10 | Motherboard chipset: AMD A520 | Number of SATA III connectors: 4 | Supported memory clock speeds: 4600 | Audio chip: Realtek ALC897 | Motherboard chipset family: AMD | Total number of SATA connectors: 4 | RAID levels: 0 | Number of storage drives supported: 2 | Ethernet LAN (RJ-45) ports: 1 | Motherboard form factor: micro ATX | RAID levels: 1 | Supported memory clock speeds: 3000 | Maximum resolution: 3840 x 2160 pixels | Supported memory clock speeds: 1866 | Unbuffered memory: Yes | PCI Express x1 (Gen 3.x) slots: 1 | Supported memory clock speeds: 2667 | Supported memory clock speeds: 3733 | Supported memory clock speeds: 4400 | Supported memory clock speeds: 3066 | Maximum internal memory: 64 GB | Supported storage drive interfaces: PCI Express 3.0, SATA | Front panel connector: Yes | Power source type: ATX | PS/2 ports quantity: 1 | Front panel audio connector: Yes | Audio output channels: 7.1 channels | USB 2.0 connectors: 4 | Supported storage drive types: HDD & SSD | Memory channels: Dual-channel | USB 3.2 Gen 1 (3.1 Gen 1) connectors: 2 | Processor manufacturer: AMD | LAN controller: Realtek 8111H | USB 2.0 ports quantity: 2 |

The product information provided is for reference purposes only. Technical specifications, photos, descriptions and prices may change without prior notice. The manufacturer and seller are not responsible for possible data discrepancies or typographical errors. We recommend checking the current information before purchasing.

Supported memory clock speeds: 2133 | Number of chassis fan connectors: 1 | Number of M.2 (M) slots: 1 | Top Wi-Fi standard: Not available | PCI Express x16 slots: 1 | USB 3.2 Gen 1 (3.1 Gen 1) Type-A ports quantity: 4 | Chassis intrusion connector: Yes | HDMI ports quantity: 1 | ATX Power connector (24-pin): Yes | Compatible processor series: AMD Ryzen 3000 Series | Processor socket: Socket AM4 | Number of memory slots: 2 | Width: 236 mm | Ethernet LAN: Yes | Memory slots type: DIMM | Supported memory types: DDR4-SDRAM | Compatible processor series: AMD Ryzen 4000 Series | Wi-Fi: No | Compatible processor series: AMD Ryzen 5000 Series | Depth: 200 mm | Ethernet interface type: Gigabit Ethernet | Microphone in: Yes

The product information provided is for reference purposes only. Technical specifications, photos, descriptions and prices may change without prior notice. The manufacturer and seller are not responsible for possible data discrepancies or typographical errors. We recommend checking the current information before purchasing.

itworkup.co.za | sales@itworkup.co.za | +27 (11)541-9950