

InLine Smart Home door/window sensor



Model: 40152

Manufacturer: INLINE

EAN: 4043718281282

Product Code: 1552474

R1,003

Direct WiFi integration without a separate gateway:The sensor connects directly to the existing network via 2.4 GHz WiFi, enabling quick integration into existing smart home structures.

Flexible automation and scenario control:Door and window contacts can be specifically integrated into individually defined processes and trigger configurable actions when the status changes.

Reliable status monitoring in real time:The integrated magnetic contact precisely detects opening and closing processes and immediately transmits the status to the Smart Life app.

High energy efficiency with long battery life:Low standby consumption enables a service life of up to 5 years in standby mode and reduces maintenance costs.

Compact design for flexible installation:The slim sensor unit and separate magnet enable discreet installation on doors, windows or housings and can be integrated in a space-saving manner.

The InLine® Smart WiFi door/window sensor is a compact contact signal transmitter for integration into existing WiFi-based smart home environments. The connection is made directly via WiFi 2.4

The product information provided is for reference purposes only. Technical specifications, photos, descriptions and prices may change without prior notice. The manufacturer and seller are not responsible for possible data discrepancies or typographical errors. We recommend checking the current information before purchasing.

itworkup.co.za | sales@itworkup.co.za | +27 (11)541-9950

gigahertz in accordance with the IEEE802.11b/g/n standard. No additional bridge or separate gateway is required.

The sensor reacts to changes in the magnetic contact between the sensor unit and the magnet module. Opening or closing processes are detected immediately and visualised in the Smart Life app. This allows automated scenarios to be configured, for example to activate additional components or to monitor the status of defined areas.

Thanks to support for voice assistants such as Amazon Alexa and Google Assistant, the sensor can be integrated into voice-controlled smart home routines. The compact design allows for discreet installation on doors, windows or cabinet elements.

The low energy consumption of 13µA in standby mode contributes to a long battery life. With an average of 7 activations per day, the service life is up to 2 years. This reduces maintenance cycles and increases operational reliability.

Colour: white/grey

Material: ABS+PC plastic

Power consumption: 115-120mA, in standby: 13µA

Signal: WiFi 2.4GHz

WiFi standard: IEEE802.11b/g/n

Range: up to 45m (with visual contact)

Operating temperature: 0°-40°C

Operating humidity: 20%-85%

Storage temperature: 0°-60°C

Storage humidity: 0%-90%

Weight: 100g

Dimensions (LxWxH): Transmitter 71x21x22mm

Dimensions (LxWxH): Magnet 40x11x11mm

Battery: 1 x CR2

Approx. service life: 2 years (with 7 activations per day)

Approx. service life: 5 years in standby mode

App: Smart Life

Compatible with: Amazon Alexa and Google Assistant

The product information provided is for reference purposes only. Technical specifications, photos, descriptions and prices may change without prior notice. The manufacturer and seller are not responsible for possible data discrepancies or typographical errors. We recommend checking the current information before purchasing.

itworkup.co.za | sales@itworkup.co.za | +27 (11)541-9950