Digitus Line-Interactive UPS, 800 VA/480 W

Model: DN-170064-B

Manufacturer: DIGITUS

EAN: 4016032498629

Product Code: 1695049

R1,548

Surge protection features: Modem | LED indicators: Yes | Input operation voltage (min): 162 V | Number of batteries supported: 1 | Cold start: Yes | Audible alarm(s): Yes | Package height: 213 mm | Battery voltage: 12 V | Width: 101 mm | AC outlets quantity: 2 AC outlet(s) | Package width: 142 mm | Noise level: 40 dB | Audible alarm modes: Alarm when on battery, Fault, Low battery alarm, Overload alarm | Form factor: Tower | Weight: 4.35 kg | Harmonized System (HS) code: 85078000 | Operating relative humidity (H-H): 0 - 95% | Operating temperature (T-T): 0 - 40 °C | USB port: No | Surge protection: Yes | Display type: LCD | Height: 142 mm | Output frequency: 50 Hz | Power protection features: Overcharge | Power protection features: Overload | Power plug: Type F | Number of input phases: 1 | Battery capacity: 7 Ah | Input operation voltage (max): 290 V | Power protection features: Battery discharge | Depth: 298 mm | Output power capacity: 0.8 kVA | Nominal input voltage: 230 V | Product colour: Black | Number of output phases: 1 | Auto-restart: Yes | Output voltage regulation: 10% | Input frequency: 50 Hz | Output power: 480 W | Package volume: 10586.1 cm³ | Automatic Voltage Regulation (AVR): Yes | UPS topology: Line-Interactive | Nominal output voltage: 230 V | Waveform: Pseudo sine | Transfer time (Line Mode to Battery Mode): 2 ms | Battery recharge time (90%): 6 h | UK Trade Tariff code: 85044085 | Warnings: Use the appliance in well-

The product information provided is for reference purposes only. Technical specifications, photos, descriptions and prices may change without prior notice. The manufacturer and seller are not responsible for possible data discrepancies or typographical errors. We recommend checking the current information before purchasing.
itworkup.co.za | sales@itworkup.co.za | +27 (11)541-9950

ventilated areas to avoid overheating. | Warnings: Do not disassemble the unit housing, there may be a risk of electric shock. | Warnings: Keep away from sources of fire and water.

The product information provided is for reference purposes only. Technical specifications, photos, descriptions and prices may change without prior notice. The manufacturer and seller are not responsible for possible data discrepancies or typographical errors. We recommend checking the current information before purchasing.
itworkup.co.za | sales@itworkup.co.za | +27 (11)541-9950