



DETECTOR WRL FIREPROTECT/BLA 38104 AJAX



Model: 38104

Manufacturer: AJAX

EAN: 4823114014888

Product Code: 407005

R3,137

FireProtect

Wireless fire detector with temperature sensor that monitors security in the room twenty four hours a day and immediately notifies of smoke and sharp jumps in temperature.

Registers smoke and sharp jumps in temperature in the room

Can operate independently from Ajax Hub, notifying of danger by means of a built-in siren

Independently tests the smoke chamber and gives prompt notification of the need to dust

Principle of operation

The device detects smoke by means of a camera with photoelectric sensor. If no smoke is emitted, the additional detector registers temperature increase in the room.

The product information provided is for reference purposes only. Technical specifications, photos, descriptions and prices may change without prior notice. The manufacturer and seller are not responsible for possible data discrepancies or typographical errors. We recommend checking the current information before purchasing.

itworkup.co.za | sales@itworkup.co.za | +27 (11)541-9950

Features

It can operate independently from the hub, emitting a fire alarm by means of a built-in siren. Several detectors indicate an alarm simultaneously.

Installation and set up

Ready to operate straight out the box: the battery is already installed, therefore there is no need to disassemble the detector. With one click, it can be connected to the hub in the mobile application. It can be mounted on the SmartBracket in just a few minutes.

- Authentication to prevent forgery
- Jamming detection and communication channels encryption
- Tampering alarm

Summary: Ajax FireProtect Jeweller. Detector type: Photoelectrical reflection detector, Connectivity technology: Wireless, Product colour: Black. Power source: Battery, Battery voltage: 3 V. Width: 132 mm, Depth: 31 mm, Height: 132 mm. Quantity per pack: 1 pc(s). Compliance certificates: CE | Vendor Homepage: <https://ajax.systems/products/fireprotect/> | Alarm decibels: 85 | Bandwidth: 868 | Best uses: Home | Connectivity technology: Wireless | Detector type: Photoelectrical reflection detector | False alarm protection: Yes | Interconnectable: Yes | International Protection (IP) code: IP40 | LED indicators: Yes | Mounting type: Surface-mounted | Placement supported: Horizontal | Product colour: Black | Suitable for indoor use: Yes | Backup battery: Yes | Battery voltage: 3 | Number of batteries supported: 2 | Power source: Battery | Operating relative humidity (H-H): 0 - 80 | Operating temperature (T-T): 0 - 65 | Depth: 31 | Height: 132 | Weight: 220 | Width: 132 | Batteries included: Yes | Compliance certificates: CE | Manual: Yes | Mounting kit: Yes | Quantity per pack: 1 | Product Net Weight: 0.22 | Shipping Box Height: 25.5 | Unit Calculated Volume: 0.001621 | Unit Calculated Weight: 0.294 | Units per Shipping Box: 20 | Model name: FireProtect Jeweller