

**KEMOT
PROsinus-500
emergency
power supply a
pure sine wave
inverter with a
12V charging
function, 230V,
500VA/300W**



Model: URZ3404

Manufacturer: KEMOT

EAN: 5901890013086

Product Code: 971368

R2,318

Input operation voltage (min): 190 V | Output operation voltage (min): 200 V | Output power capacity: 500 VA | Height: 180 mm | Product colour: White | Output power: 300 W | DC battery voltage: 12 V | AC outlets quantity: 2 AC outlet(s) | Automatic Voltage Regulation (AVR): Yes | Input frequency: 50/60 Hz | Warnings: Do not disassemble the unit housing, there may be a risk of electric shock. | Warnings: Keep away from sources of fire and water. | AC outlet types: Schuko | Power protection features: Short circuit | Power protection features: Over voltage | Supported battery type:

The product information provided is for reference purposes only. Technical specifications, photos, descriptions and prices may change without prior notice. The manufacturer and seller are not responsible for possible data discrepancies or typographical errors. We recommend checking the current information before purchasing.

itworkup.co.za | sales@itworkup.co.za | +27 (11)541-9950

AGM / Gel | Depth: 240 mm | Power protection features: Overload | Waveform: Pure sine | Width: 145 mm | Warnings: Use the appliance in well-ventilated areas to avoid overheating. | Power efficiency: 85% | Output frequency: 50/60 Hz | Response time: 4 ms | Weight: 4.3 kg | USB port: No | Input operation voltage (max): 260 V | Output operation voltage (max): 245 V | Battery included: No

The product information provided is for reference purposes only. Technical specifications, photos, descriptions and prices may change without prior notice. The manufacturer and seller are not responsible for possible data discrepancies or typographical errors. We recommend checking the current information before purchasing.

itworkup.co.za | sales@itworkup.co.za | +27 (11)541-9950